ET-60 Air Bath

Air Incubator

Introduction

The air bath is one multipurpose incubator built in micro-processor with PID controlling. It is suitable for sample incubating in micro-plates, Gel cards, beakers, culture dishes, etc.

Feature

- 1. It looks neat and concise. Transparent cover makes experimentation visible. LED display temperature and time.
- 2. Various sample containers such as micro-plate, reagent cards frame, beaker, culture dish, etc, which can be put into the incubation space.
- 3. Micro-processor controls temperature and time. Temperature control with good linear, small fluctuation.
- 4. Safe and reliable. Beep alarm when time ends.



Accessories





ET-PLT ET-GCD



ADDRESS OF THE PERSON NAMED IN

Parameter

| Model | ET-60 | Fan Speed Range | 1200~3200rpm |
|------------------------|---------------|-----------------------|--------------------------|
| Temp. Control Range | R.T.+5°C~60°C | Incubation Space Size | L.245 x W.215 x H.85mm |
| Temp. Setting Range | 5℃~60℃ | Voltage | AC 220V/AC 110V, 50/60Hz |
| Temp. Stability@37℃ | ±0.2℃ | Power | 300W |
| Temp. Uniformity | ±0.5℃ | Fuse | 250V, 2A/4A, Φ5×20 |
| Temp. Display Accuracy | 0.1℃ | Dimension | W.275 x D.395 x H.150mm |
| Time Range | 1min~99h59min | Net Weight | 8.1kgs |